



February 2, 2015

Replacement of Z-ION Generator Bowl

First, replace the filter bowl and, if needed, the carbon filter (sold separately). Reconnect the generator cable.

Next, when the Z-ION generator is worn out and needs to be replaced, the cycle counter in the electronic controller needs to be reset to its original state. To do this, open the controller enclosure to access the electronic board. In the kit will be two magnets. With power applied (the green led should be lit) Place each of the two magnets next to the switches one and two. Remove the magnets. Now you should be ready for another 360 cycles of operation.

Z-ION Board Layout

